

FUTURE VISION BIE

One Stop for All Study Materials
& Lab Programs



Future Vision

By K B Hemanth Raj

Scan the QR Code to Visit the Web Page



Or

Visit : <https://hemanthrajhemu.github.io>

Gain Access to All Study Materials according to VTU,
CSE – Computer Science Engineering,
ISE – Information Science Engineering,
ECE - Electronics and Communication Engineering
& MORE...

Join Telegram to get Instant Updates: https://bit.ly/VTU_TELEGRAM

Contact: MAIL: futurevisionbie@gmail.com

INSTAGRAM: www.instagram.com/hemanthraj_hemu/

INSTAGRAM: www.instagram.com/futurevisionbie/

WHATSAPP SHARE: <https://bit.ly/FVBIESHARE>

USN

--	--	--	--	--	--	--	--	--	--

10EC/TE61

Sixth Semester B.E. Degree Examination, June/July 2019

Digital Communication

Time: 3 hrs.

Max. Marks:100

Note: Answer any FIVE full questions, selecting at least TWO questions from each part.

PART – A

1.
 - a. Compare analog and digital communication. (04 Marks)
 - b. Derive the interpolation formula for reconstructing the original signal from the sequence of sampled values. (08 Marks)
 - c. The signal $x(t) = 12 \cos(800\pi t) \cos^2 1800\pi t$ is ideally sampled at 4600 samples/sec. What is the minimum allowable sampling frequency? What is the range of the cut-off frequency for the lowpass filter? Draw the frequency components present in the output of the lowpass filter. (08 Marks)
2.
 - a. Derive an expression for output SNR of the quantizer and show that $(SNR)_0 = 1.76 + 6n$ in db if a sinusoidal signal is quantized. (08 Marks)
 - b. What is the need for non-uniform quantization? Explain μ -law and A-law compounding. (08 Marks)
 - c. A PCM system uses a uniform quantizer followed by a 7 bit binary encoder. The bit rate of the system is equal to 50×10^6 bits/sec:
 - i) What is the sampling frequency?
 - ii) Calculate the $(SNR)_0$. (04 Marks)
3.
 - a. What is slope overload distortion and granular noise in delta modulation and how can it be reduced? (08 Marks)
 - b. Obtain the expression for power spectral density of NRZ unipolar format. (06 Marks)
 - c. Explain T1 carrier system. (06 Marks)
4.
 - a. Explain ISI. Derive an expression for Nyquist pulse shaping criterion for distortionless baseband binary transmission. (08 Marks)
 - b. Explain eye pattern. (06 Marks)
 - c. A continuous time signal is connected into a PCM wave. The number of quantization levels = 64. A synchronizing pulse is added at the end of each code word representing a sample of the analog signal. The resulting PCM is sent over a channel of bandwidth 24 kHz using a binary PAM system with raised cosine spectrum with roll off = 1.
 - i) Find the bit rate
 - ii) Find the sampling rate
 - iii) What is the highest frequency of the continuous time signal? (06 Marks)

PART – B

5.
 - a. With a block diagram, explain coherent QPSK transmitter and receiver. (08 Marks)
 - b. Explain non-coherent DPSK system. (06 Marks)
 - c. For a given binary sequence 01101000 sketch the inphase and quadrature phase components of QPSK. Adding these two get the final waveform. (06 Marks)

- 6 a. Explain the two stage Gram-Schmidt orthogonalization procedure to find the orthonormal functions. (10 Marks)
- b. Derive the equation for maximum likelihood estimation. (10 Marks)
- 7 a. List the properties of a matched filter receiver. (08 Marks)
- b. Show that the probability of bit error of a matched filter receiver is given by
- $$P_e = \frac{1}{2} \operatorname{erfc} \sqrt{\frac{E_b}{N_0}} \quad (08 \text{ Marks})$$
- c. Let $s(t)$ be a rectangular pulse of amplitude A and duration T seconds, applied to the input of a filter matched to $s(t)$. Determine the output signal to noise ratio of the filter at $t = T$ in terms of noise power spectral density. (04 Marks)
- 8 a. What is spread spectrum? Explain the principle of direct sequence spread spectrum system. (08 Marks)
- b. Explain the properties of PN sequence. (06 Marks)
- c. In a DSSS it is required to have a jamming margin greater than 26 dB. The ratio E_b/N_0 is set at 10. Determine the minimum processing gain and the minimum number of stages required to generate the maximum length of sequence. (06 Marks)

* * * * *